



IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS

Installation instructions for Prologe 80 in-Line and in-Dolma. Model numbers: ku(x)96511_, ku96513_, ku(x)96521_, ku96523_, ku96512x and ku96522x

 **WARNING:** READ AND UNDERSTAND ALL INSTRUCTIONS BEFORE STARTING INSTALLATION. SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE

 **RISK OF FIRE! - RISK OF SHOCK!**

- INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS
THIS LUMINAIRE MUST BE INSTALLED TO CONFIRM WITH NEC AND ALL LOCAL ELECTRICAL & BUILDING CODES & PRACTICES. TO ASSURE

FULL COMPLIANCE WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL INSPECTOR BEFORE INSTALLATION.


- DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING
- ENSURE THE LUMINAIRE IS GROUNDED
- LUMINAIRE MAY NOT COME IN CONTACT WITH INSULATION. ANY INSULATION IS A MINIMUM OF 3" AWAY FROM HOUSING.
- NON IC TYPE LUMINAIRE
- BLINKING LIGHT OF THIS THERMALLY PROTECTED LUMINAIRE MAY INDICATE OVERHEATING
- SUITABLE FOR INDOOR DRY LOCATIONS ONLY
- SUITABLE FOR INDOOR DRY LOCA-

TIONS ONLY
- SUPPLY CONDUCTORS (POWER WIRES) CONNECTING THE LUMINAIRE MUST BE RATED 90°C
- CAUTION - TO REDUCE RISK OF FIRE, DO NOT USE LAMP IDENTIFIED FOR USE IN ENCLOSED LUMINAIRES ONLY

WARNING - to reduce the risk of FIRE OR INJURY:
- turn off power and allow to cool before replacing lamp
- lamp gets HOT quickly! contact only switch/plug when turning on
- do not touch hot lens, guard, reflector or enclosure
- keep lamp away from materials that may burn
- do not touch lamp at any time; use soft cloth; oil from skin may damage the lamp

- do not operate the luminaire with a missing or damaged shield, if required


This luminaire can only be used with Kreon accessories.

 = **CAUTION - RISK OF FIRE** - do not install a lamp identified for use only in enclosed luminaires

This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

1 notifications

Notice de montage pour Prologe 80 in-Line and in-Dolma.

 **ATTENTION:** LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES

 **RISQUE D'INCENDIE!**
RISQUE DE CHOC!


- INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE
- CE PRODUIT DOIT ETRE INSTALLE SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAIT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHERENTS
- CONSULTER UN ELECTRICIEN QUALIFIE POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DERIVA-

TION SONT ADEQUATS
- COUPER L'ALIMENTATION AVANT L'ENTRETIEN
- ASSURER QUE LE LUMINAIRE EST MIS A LA TERRE
- SI L'AMPOULE DE CE LUMINAIRE A PROTECTION THERMIQUE CLIGNOTE, CELA PEUT SIGNIFIER UNE SURCHAUFFE
- NE PAS METTRE L'ISOLANT A MOINS DE 3" DE TOUTE PARTIE DU LUMINAIRE
- POUR EMPLACEMENT SECS SEULEMENT

ALERTE - pour réduire le risque D'INCENDIE OU DE BLESSURE:
- coupez l'alimentation électrique et laissez refroidir avant de remplacer l'ampoule
- la lampe chauffe rapidement!
- ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte

- gardez le luminaire loin de matériaux qui peut brûler
- ne jamais touchez l'ampoule; utilisez un chiffon doux; l'huile de la peau peut endommager l'ampoule
- luminaires équipés avec un verre de sécurité doivent operé d'un verre de sécurité complet et en place














Le luminaire ne peut être utilisé qu' avec des accessoires de Kreon

 = **ATTENTION - RISQUE D'INCENDIE** - ne pas utiliser une ampoule conçue seulement pour des luminaires fermés

Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.

1 notifications

technics	<p>In-Line and In-Dolma : Prologe 80</p> <div data-bbox="436 255 1232 430"> </div>	<table> <tr> <th>Name</th><th>Reference</th><th>L x W x H</th></tr> <tr> <td>Prologe 80 in-Line / in-Dolma Single</td><td>ku(x)96511_, ku96513_</td><td>3" x 3" x 4"</td></tr> <tr> <td>Prologe 80 in-Line / in-Dolma Double</td><td>ku(x)96521_, ku96523_</td><td>5 7/8" x 3" x 4"</td></tr> <tr> <td>Prologe 80 in-Line / in-Dolma Single</td><td>ku96512x</td><td>3" x 3" x 4"</td></tr> <tr> <td>Prologe 80 in-Line / in-Dolma Double</td><td>ku96522x</td><td>5 7/8" x 3" x 4"</td></tr> </table>	Name	Reference	L x W x H	Prologe 80 in-Line / in-Dolma Single	ku(x)96511_, ku96513_	3" x 3" x 4"	Prologe 80 in-Line / in-Dolma Double	ku(x)96521_, ku96523_	5 7/8" x 3" x 4"	Prologe 80 in-Line / in-Dolma Single	ku96512x	3" x 3" x 4"	Prologe 80 in-Line / in-Dolma Double	ku96522x	5 7/8" x 3" x 4"
Name	Reference	L x W x H															
Prologe 80 in-Line / in-Dolma Single	ku(x)96511_, ku96513_	3" x 3" x 4"															
Prologe 80 in-Line / in-Dolma Double	ku(x)96521_, ku96523_	5 7/8" x 3" x 4"															
Prologe 80 in-Line / in-Dolma Single	ku96512x	3" x 3" x 4"															
Prologe 80 in-Line / in-Dolma Double	ku96522x	5 7/8" x 3" x 4"															
2 dimensions	<p>Prologe 80 Single Prologe 80 Double Prologe 80 in-Line Prologe 80 in-Dolma</p>	<table> <tr> <th>Name</th><th>Reference</th><th>L x W x H</th></tr> <tr> <td>Custom length in-Line Profile</td><td>ku765102, ku765103</td><td>(L + 2/5") x 4 1/8" x 9 3/5"</td></tr> <tr> <td>Custom length in-Dolma Profile</td><td>ku765002, ku765003</td><td>(L + 2/5") x 4 1/8" x 7 1/2"</td></tr> </table>	Name	Reference	L x W x H	Custom length in-Line Profile	ku765102, ku765103	(L + 2/5") x 4 1/8" x 9 3/5"	Custom length in-Dolma Profile	ku765002, ku765003	(L + 2/5") x 4 1/8" x 7 1/2"						
Name	Reference	L x W x H															
Custom length in-Line Profile	ku765102, ku765103	(L + 2/5") x 4 1/8" x 9 3/5"															
Custom length in-Dolma Profile	ku765002, ku765003	(L + 2/5") x 4 1/8" x 7 1/2"															
3 installation	<div data-bbox="526 518 996 798"> </div> <p>hang the profile with the safety brackets to the primary ceiling</p>																
4 installation	<div data-bbox="515 861 739 1069"> </div> <p>choose a knock-out, push out and connect lead cable</p> <div data-bbox="862 901 1265 1069"> </div> <p>install plasterboard around the profile</p>	<div data-bbox="1332 853 1612 1109"> </div> <p>slide perforated brackets into gap</p> <div data-bbox="1736 893 2083 1093"> </div> <p>and fix with plasterboard screws</p>															
5 installation	<div data-bbox="436 1181 1019 1420"> </div> <p>line out the profile with the plasterboard by turning the black screws in the profile in the correct order</p>	<div data-bbox="1321 1181 1848 1436"> </div> <p>finish with plaster; kreon recommends polyester filler 2K</p>															
kreon nv																	

<p>technics</p>		<ul style="list-style-type: none"> - connect black supply wire with black wire in profile - connect white supply wire with white wire in profile - connect green earthing wire with green earthing wire in profile <p>connect supply wires with proper size wire nuts after connection replace cover so all wiring and connections are enclosed in profile</p>	<p><u>In case of low voltage lamps</u></p> 	<p><u>In case of line voltage lamps</u></p> 
<p>6 installation</p>	<p>make cable connection in the profile</p> <p><u>In case of LED on/off</u></p> 	<p><u>In case of LED 0-10V dimming</u></p> 	<p><u>In case of Lutron LED EcoSystem digital control</u></p> 	<p>connect supply wires to fixtures</p> <p>connect supply wires to fixture</p>
<p>7 connection</p>				<p>close the profile with provided covers make sure they are fastened</p>
<p>8 installation</p>	<p>click chassis of the luminaires on its right place and make connection in the profile</p> <p>frosted glass</p> 	<p>click housing on the chassis insert louvre in housing</p> 		
<p>9 accessories + pictures</p>	<p>slide the glass in the louvre</p>	<p>fold lips around glass</p>	<p>www.kreon.com usa@kreon.be</p>	<p>Rev. date :16/05/2014 KR8650001708</p>
<p>kreon inc</p>		<p>Tel 646 213 7487 Fax 646 213 1456</p>		