



IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS

Installation instructions for Prologe 80 in-Line and in-Dolma. Model numbers: ku96575_, ku96595_, ku(x)96576_, ku(x)96596_

 **WARNING:** READ AND UNDERSTAND ALL INSTRUCTIONS BEFORE STARTING INSTALLATION. SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE

 **RISK OF FIRE! - RISK OF SHOCK!**

- INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS
THIS LUMINAIRE MUST BE INSTALLED TO CONFIRM WITH NEC AND ALL LOCAL ELECTRICAL & BUILDING CODES & PRACTICES. TO ASSURE

FULL COMPLIANCE WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL INSPECTOR BEFORE INSTALLATION.

- DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING
- ENSURE THE LUMINAIRE IS GROUNDED
- LUMINAIRE MAY NOT COME IN CONTACT WITH INSULATION. ANY INSULATION IS A MINIMUM OF 3" AWAY FROM HOUSING.
- NON IC TYPE LUMINAIRE
- BLINKING LIGHT OF THIS THERMALLY PROTECTED LUMINAIRE MAY INDICATE OVERHEATING
- SUITABLE FOR INDOOR DRY LOCATIONS ONLY
- SUITABLE FOR INDOOR DRY LOCA-


TIONS ONLY
- SUPPLY CONDUCTORS (POWER WIRES) CONNECTING THE LUMINAIRE MUST BE RATED 90°C
- CAUTION - TO REDUCE RISK OF FIRE, DO NOT USE LAMP IDENTIFIED FOR USE IN ENCLOSED LUMINAIRES ONLY

WARNING to reduce the risk of FIRE OR INJURY:

- turn off power and allow to cool before replacing lamp
- lamp gets **EXTREMELY** hot quickly! contact only switch/plug when turning on
- do not touch hot lens, guard, reflector or enclosure
- keep lamp away from materials that may burn
- do not touch lamp at any time; use soft cloth; oil from skin may damage the lamp

- do not operate the luminaire with a missing or damaged shield if required


This luminaire can only be used with Kreon accessories.

 = **CAUTION - RISK OF FIRE** - do not install a lamp identified for use only in enclosed luminaires

This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

1 notifications

Notice de montage pour Prologe 80 in-Line and in-Dolma.

 **ATTENTION:** LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES

 **RISQUE D'INCENDIE! RISQUE DE CHOC!**


- INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE
- CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS
- CONSULTER UN ÉLECTRICIEN QUALIFIÉ POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DERIVA-

TION SONT ADEQUATS
- COUPER L'ALIMENTATION AVANT L'ENTRETIEN
- ASSURER QUE LE LUMINAIRE EST MIS À LA TERRE
- SI L'AMPOULE DE CE LUMINAIRE A PROTECTION THERMIQUE CLIGNOTE, CELA PEUT SIGNIFIER UNE SURCHAUFFE
- NE PAS METTRE L'ISOLANT À MOINS DE 3" DE TOUTE PARTIE DU LUMINAIRE
- POUR EMPLACEMENT SECS SEULEMENT

ALERTE - pour réduire le risque D'INCENDIE OU DE BLESSURE:
- coupez l'alimentation électrique et laissez refroidir avant de remplacer l'ampoule
- la lampe chauffe rapidement!
- ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte

- gardez le luminaire loin de matériaux qui peut brûler
- ne jamais touchez l'ampoule; utilisez un chiffon doux; l'huile de la peau peut endommager l'ampoule
- luminaires équipés avec un verre de sécurité doivent être opérés d'un verre de sécurité complet et en place

Le luminaire ne peut être utilisé qu'avec des accessoires de Kreon


 = **ATTENTION - RISQUE D'INCENDIE** - ne pas utiliser une ampoule conçue seulement pour des luminaires fermés

Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.

1 notifications


technics

In-Line and In-Dolma : Prologe 80 T5



Name	Reference	L x W x H
Prologe 80 in-Line / in-Dolma T5HO	ku96595_	35 1/2" x 3" x 4"
Prologe 80 in-Line / in-Dolma T5HO	ku96575_	35 1/2" x 3" x 4"
Prologe 80 in-Line / in-Dolma T5HO	ku96576_	47 1/4" x 3" x 4"
Prologe 80 in-Line / in-Dolma T5HO	ku96596_	47 1/4" x 3" x 4"

2 dimensions



hang the profile with the safety brackets to the primary ceiling

Name	Reference	L x W x H
Custom length in-Line Profile	ku765102ku765103	(L+2/5") x 4 1/8" x 9 5/8"
Custom length in-Dolma Profile	ku765002ku765003	(L+2/5") x 4 1/8" x 7 1/2"


3 installation

choose a knock-out, push out and connect lead cable


install plasterboard around the profile

slide perforated brackets into gap

and fix with plasterboard screws




line out the profile with the plasterboard by turning the black screws in the profile in the correct order



finish with plaster; kreon recommends polyester filler 2K


4 installation




5 installation

install the security brackets in the slots of the long plate and twist 90° while placing in the profile


profile section view



fasten the brackets to the long plate with screws




plug cable in female connector according to the wiring scheme




6 installation

connect female with male connector; slide housing over chassis and screw the luminaire to the installed plate




place lamp and insert louvre in housing

in case of Prologe 80 T5HO 39W



in case of Prologe 80 T5HO 54W dimmable



7 picture

The luminaire can only be used with Kreon accessories.

This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

kreon nv

Industrieweg Noord 1152
B 3660 Opglabbeek
Belgium

Tel + 32 89 81 97 80
Fax + 32 89 81 97 90

www.kreon.com
mailbox@kreon.be

Rev. date :16/10/2012
KU8657601817 page 3/3