


kreon

technics



Name

Aplis 40 fixed
Aplis 40 WW

Reference

KR95703x, KR96703x, KR97703x, KR98703x
KR95733x


Drive current

700mA
700mA

The luminaire must not under any circumstances be covered with heat insulating covers or similar materials.
Cables must not touch the luminaire housing.
The connection cable must be routed so that it does not touch the lamp when the luminaire is tilted.

1 dimensions

in case of platerboard ceiling



Name

Aplis 40 fixed
Aplis 40 WW

Reference

KR95703x, KR96703x, KR97703x, KR98703x
KR95733x

A

Ø 45
Ø 45

ExF

110x110
110x110

G_{min}


80
80

T_{min}-T_{max}


9-26
9-26

Please make sure that
main voltage is disconnected
before proceeding! ⚡


2 cut out




Remove louvre and module.



Fold the springs against the ring and rotate
anti clockwise to insert into the ceiling.




Put the module on the louvre to install the module.




In case of transformer or ballast.

3 installation





Put the assembly in the plasterkit until the louvre clicks,
see also manual KR8170001761.



Lightbeam

In case of WW



Fixed

WW

4 installation

revision date:17-04-2015

Sheet 1/1