

IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS

Installation instructions for REI recessed profile ku98354_

Read the label on the luminaire for information on the dimming.

! WARNING: READ AND UNDERSTAND ALL INSTRUCTIONS BEFORE STARTING INSTALLATION. SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE

! RISK OF FIRE! - RISK OF SHOCK!

- INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS
- THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A

PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED
TO ASSURE FULL COMPLIANCE WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL INSPECTOR BEFORE INSTALLATION.

- DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING
- IC TYPE LUMINAIRE
- SUITABLE FOR DRY LOCATIONS
- SUPPLY CONDUCTORS (POWER WIRES) CONNECTING THE LUMINAIRE MUST BE RATED 90°C
- INHERENTLY PROTECTED

WARNING: to reduce the risk of FIRE OR INJURY:

- turn off power and allow to cool before replacing lamp
- lamp gets HOT quickly
- do not touch hot lens, guard, reflector or enclosure
- to reduce the risk of fire and overheating, make sure all connections are tight

This luminaire can only be used with Kreon accessories.

This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

1 notifications

Notice de montage pour REI profil en creux ku98354_
Lisez l'étiquette sur le luminaire pour information à propos de gradation

! ATTENTION: LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES

**! RISQUE D'INCENDIE!
RISQUE DE CHOC!**


- INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE
- CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS

- CONSULTER UN ELECTRICIEN QUALIFIE POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DERIVATION SONT ADEQUATS
- COUPER L'ALIMENTATION AVANT L'ENTRETIEN
- TYPE IC
- CONVIENT AUX EMPLACEMENTS SECS
- LES FILS D'ALIMENTATION DOIVENT CONVENIR POUR 90°C
- PROTECTION INHÉRENTE










ALERTE - pour réduire le risque D'INCENDIE OU DE BLESSURE:
- coupez l'alimentation électrique et laissez refroidir avant de remplacer l'ampoule
- la lampe chauffe rapidement!
- ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte

Le luminaire ne peut être utilisé qu' avec des accessoires de Kreon

Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.



1 notifications

	technics		name	reference	LxWxH	Vin	LED drive current	max. W
		Rei Recessed Mounted	Rei recessed mounted	KU98354x	Lx22/8" x 26/8"	120-277V	500mA	7W/ft.
2	dimensions		REI LED profile luminaires can be dimmed 0-10V or DALI - read the label on the luminaire for correct information					
3	installation recessed mounted Rei	 to install the plasterkit see installation manual KR8830401974	 connect female connector with strain relief to power supply and dim channel	 make correct connection with male connector in the luminaire.				
4	installation recessed mounted Rei	 close the unused connectors at the opposite side with the included female connectors	 add cable to fall safety at both ends	 place Rei recessed profile				
5	installation recessed mounted Rei	 click ! click ! make sure the luminaire clicks on the springs	 in case of several pieces, repeat previous steps for all pieces. CAUTION: match the luminaire parts with the corresponding plasterkits!					

technics		<p>push allen key completely in the hole</p> <p>insert allen key at both sides CAUTION: support the profile to avoid falling!</p>
6 installation recessed mounted Rei	to remove the Rei profile, use tool as shown	
7 installation recessed mounted Rei	<p>pull the inserted tools on both sides simultaneously to remove the inner part - keep both allen keys inserted while removing the luminaire</p>	<p>luminaire can be taken out of the installed recessed profile</p> <p>to remove cable from fall safety at both ends</p>
8 installation recessed mounted Rei	<p>In case of accessory KR783540: suction cup</p> <p>add a suction cup at both ends - insert allen key at both sides - CAUTION: support the profile to avoid falling</p>	<p>pull both suction cups simultaneously to remove the inner part out of the ceiling.</p> <p>push allen key completely in the hole</p> <p>keep both allen keys inserted while removing the luminaire</p>
9 installation recessed mounted Rei	<p>supply voltage 120-277V</p> <p>LED driver</p> <p>white — N green — earth black — L</p> <p>dimming: ATTENTION: check polarity in case of 0-10V</p> <p>grey — + / DA violet — - / DA</p> <p>to LED strips</p> <p>red — + black — - red — + black — -</p> <p>connection scheme</p>	<p>Lightbeam</p> <p>Wall</p> <p>Light</p> <p>make sure the the lightbeam is directed correctly - in case of a wallwasher, light is directed to the wall</p>
kreon inc	Tel 646 213 7487 Fax 646 213 1456	www.kreon.com usa@kreon.com
revision date: 05/03/2013 KR8835401943	p.3/3	