

IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS

Installation instructions for KREON -
ONN WALL 165/300 LED, gear inclusive
ku98331x, kx98332x

**! WARNING: READ AND UNDER-
STAND ALL INSTRUCTIONS
BEFORE STARTING INSTALLATION.
SAVE THESE INSTRUCTIONS FOR
FUTURE REFERENCE**

RISK OF FIRE! - RISK OF SHOCK!

- INSTRUCTIONS PERTAINING TO A
RISK OF FIRE OR INJURY TO PERSONS
- THIS LUMINAIRE MUST BE
INSTALLED TO CONFIRM WITH NEC
AND ALL LOCAL ELECTRICAL &
BUILDING CODES & PRACTICES. TO
ASSURE FULL COMPLIANCE WITH

LOCAL CODES AND REGULATIONS,
CONSULT WITH YOUR LOCAL
ELECTRICAL INSPECTOR BEFORE
INSTALLATION
- DISCONNECT POWERSUPPLY
BEFORE INSTALLING OR SERVICING
- ENSURE THE LUMINAIRE IS
GROUNDED

- LUMINAIRE IS WALL MOUNTED
ONLY
- SUITABLE FOR DAMP LOCATION

WARNING
to reduce the risk of FIRE OR INJURY:
- turn off power and allow to cool
before replacing lamp

1 notifications

- lamp gets HOT quickly! contact only
switch/plug when turning on
- do not touch hot lens, guard,
reflector or enclosure
- keep luminaire away from materials
that may burn

The luminaire can only be used with
Kreon accessories.

This installation manual might not
cover all details or variations. When
additional information is required,
please contact your local representa-
tive, or one of the Kreon offices.

Notice de montage pour KREON -
ONN WALL, auxiliaire inclus
ku98331x, kx98332x

**! ATTENTION: LIRE ET COM-
PRENDRE TOUTES LES INSTRUC-
TIONS AVANT L'INSTALLATION
CONSERVER CES INSTRUCTIONS
POUR DE FUTURES REFERENCES**

**! RISQUE D'INCENDIE!
RISQUE DE CHOC!**

- INSTRUCTIONS RELATIVES À UN
RISQUE D'INCENDIE OU DE BLESSURE
- CE PRODUIT DOIT ETRE INSTALLE
SELON LE CODE D'INSTALLATION
PERTINENT, PAR UNE PERSONNE QUI
CONNAIT BIEN LE PRODUIT ET SON
FONCTIONNEMENT AINSI QUE LES
RISQUES INHERENTS
- CONSULTER UN ELECTRICIEN
QUALIFIE POUR VOUS ASSURER QUE
LES CONDUCTEURS DE LA DERIVA-
TION SONT ADEQUATS

2

- COUPER L'ALIMENTATION AVANT
L'ENTRETIEN
- ASSURER QUE LE LUMINAIRE EST
MIS A LA TERRE
- MONTER LE LUMINAIRE EN SURFACE
SEULEMENT
- CONVIENTS AUX EMPLACEMENTS
HUMIDES



ALERTE
pour réduire le risque D'INCENDIE OU
DE BLESSURE:

- coupez l'alimentation électrique et
laisser refroidir avant de remplacer
l'ampoule
- la lampe chauffe rapidement!
- ne touchez pas l'objectif à chaud, la
garde, le réflecteur ou une enceinte
- gardez le luminaire loin de matériaux
qui peut brûler

Le luminaire ne peut être utilisé qu' avec
des accessoires de Kreon.

Cette notice de montage ne couvre pas
tous les détails ou les variations. Pour
des informations supplémentaires veuillez
contacter votre représentant local ou un
des bureaux Kreon.

3






recommended orientation

Name	Reference	LxHxW	Voltage	Drive current	max. W	A
Onn wall 165	KU98331x	8"x1 3/8"x6 1/2"	120V	350mA	8,7W	114
Onn wall 300	KU98332x	8"x1 3/8"x11 7/8"	120V	700mA	17,4W	249

4 Dimensions

technics




1

dimensions


Remove the two screws with a screw driver.

Slide the two allen keys into the holes to open the fixture.

Remove the housing.



Please make sure that
main voltage is disconnected
before proceeding!






2

installation

Disconnect the connector.

1. screw plasterkit on the octagonal
junction- box size 4
2. pull wire through hole and finish with
plaster






3

installation

Supply power from wall and drill two installation holes.

Rotate the mounting plate with LED-driver 90° down.

Pull power supply cable through hole.



4




installation

Screw the mounting assembly with the fixation extrusion to the wall.

Remove the plastic cover.

Connect powersupply and/or dali dim.

technics





5 installation

Place the plastic cover back and fix it with the screws.

Rotate the mounting plate with LED-driver horizontally.

Connect the connector.



6 installation

Close the housing until it clicks over the springs.

Fix the two screws with an screw driver.

7 pictures

