


kreon installation manual

technics & dimensions




Lamp not included.
Only LED lamp allowed, no halogen!

Name	Reference	Voltage ⚡	B (Soora lamp added)	Max wattage
Down 80 directional led mr16	KR94780x	12V	97	15 W
Down 80 directional led par16	KR94784x	230V	117	15 W
Down 80 fixed led mr16	KR94723x	12V	97	15 W
Down 80 fixed led par16	KR94725x	230V	117	15 W


The luminaire must not under any circumstances be covered with heat insulating covers or similar materials.
Cables must not touch the luminaire housing.
The connection cable must be routed so that it does not touch the lamp when the luminaire is tilted.

cut-out




Name	Reference	A x B	CxD	E _{min}	FxG	H _{min}	T _{min} -T _{max}
Down 80 directional led mr16	KR94780x	91x91	230x230	110	350x350	110	
Down 80 directional led par16	KR94784x	91x91	230x230	130	330x330	130	
Down 80 fixed led mr16	KR94723x	91x91	230x230	110	350x350	110	
Down 80 fixed led par16	KR94725x	91x91	230x230	130	330x330	130	
Plasterboard thickness							9-26

1. installation



Insert lamp into socket with springs.

Please make sure that
main voltage is disconnected
before proceeding! ⚡




In case of transformer or driver.


kreon installation manual

2. installation

In case of directional part




Push at the filterholder to rotate inner part manually.




Turn innerpart manually.

In case of relamping




Remove the louvre (use tool in case of fixed).


3. installation




Bend springs to remove directional part



Remove inner part.




Replace lamp.



Add inner part.

4. installation



Insert the louvre in the plasterkitbox.

