


technics

Nuit



Please make sure that mains voltage is disconnected before installing!

Name

Nuit profile system

Reference

kr70311_

L x W x H

L x 40 x 53

Attention:

- make sure there is one connection per Nuit profile section.
- in case of the use of an emergency kit, make sure the emergency is on a separate circuit and having permanently voltage

1 dimensions


Name	Driver	Mains input	LED Wattage	ConstantCurrent
Nuit LED module	incl. (DALI or 1-10V)	230Vac	8.5W per 5 LED's	500mA
Nuit EM LED module	incl.* + battery pack (3h)	230Vac	1.5W per 5 LED's**	500mA

2 specifications


*The driver of Nuit EM LED module is a non-maintained
** EM lumenoutput is appr. 12% of normal lumenoutput

3 installation in case of surface mounting

supply correct power from ceiling (see table)
ATTENTION: switch power off while installing!




drill 2 holes(Ø5) on a same distance from the powersupply (see table)
make sure that all holes are aligned




insert plugs

4 installation in case of surface mounting

connect female connector with strain relief to powersupply



make correct connection with male connector in luminaire



insert plugs and fix luminaire to ceiling


Nuit recessed profile

Name	Reference	L x W x H
Nuit recessed profile	kr703055	L x 55 x 88


Attention:

- make sure there is one connection per 2.3m of Nuit profile.
- in case of the use of an emergency kit, make sure the emergency is on a separate circuit and having permanently voltage


Please make sure that mains voltage is disconnected before installing! ⚡




1 dimensions



fix the mounting brackets kr703056 on the recessed profile; adjust the height of the bracket according to the thickness of the ceiling to ensure a trimless mount




attach the recessed profile to hangers





install the ceiling for installation of Nuit profile; see item 5

2 installation for solid ceiling






suspend the profile using the profile snap hangers kr726057 and quick adjust hangers



install the plasterboard for installation of Nuit profile; see item 5

3 installation for dry plaster ceiling




Installation of Nuit recessed



no specifically correct way to install the support profile;
the installation procedure depends on the conditions on the
building site and your own particular desires

for installation of Nuit profile; see item 5

4 installation for
wet plaster ceiling





after installation of the plasterkit
or recessed profile, follow the next steps
Attention: make sure there is one connection
per 2.3m of Nuit profile.

use the supplied parallelogram shaped nuts
and screws with countersunk heads

set the nut on top of the screw

5 installation of
Nuit



make correct connection with male
connector in luminaire

fix the luminaire in the installed recessed profile

Nuit profile

Name


Reference

L x W x H


Nuit recessed profile

kr703055



L x 40 x 53



1 dimensions



SECTION VIEW:



2 installation in cove

a cove with dimensions of the surface mounted
Nuit is build in the ceiling
correct current is provided in the cove

dimensions of the cove:
WxH = 45mm (13/4") x 55mm (21/5")

screw Nuit surface mounted in the cove
(see manual of Nuit) and finish with plaster