














	technics	Nuit		<div>Please make sure that mains voltage is disconnected before installing! ⚡</div>	<div><div>Name</div><div>Nuit profile system</div></div> <div><div>Reference</div><div>kr70311_</div></div> <div><div>L x W x H</div><div>L x 40 x 53</div></div>															
1	dimensions		<table><tr><th>Name</th><th>Driver</th><th>Mains input</th><th>LED Wattage</th><th>ConstantCurrent</th></tr><tr><td>Nuit LED module</td><td>incl. (DALI or 1-10V)</td><td>230Vac</td><td>8.5W per 5 LED's</td><td>500mA</td></tr><tr><td>Nuit EM LED module</td><td>incl.* + battery pack (3h)</td><td>230Vac</td><td>1.5W per 5 LED's**</td><td>500mA</td></tr></table>			Name	Driver	Mains input	LED Wattage	ConstantCurrent	Nuit LED module	incl. (DALI or 1-10V)	230Vac	8.5W per 5 LED's	500mA	Nuit EM LED module	incl.* + battery pack (3h)	230Vac	1.5W per 5 LED's**	500mA
Name	Driver	Mains input	LED Wattage	ConstantCurrent																
Nuit LED module	incl. (DALI or 1-10V)	230Vac	8.5W per 5 LED's	500mA																
Nuit EM LED module	incl.* + battery pack (3h)	230Vac	1.5W per 5 LED's**	500mA																
2	specifications		<div>*The driver of Nuit EM LED module is a non-maintained</div> <div>** EM lumenoutput is appr. 12% of normal lumenoutput</div>																	
3	installation in case of surface mounting	 <div>supply correct power from ceiling (see table) ATTENTION: switch power off while installing!</div>	 <div>drill 2 holes(Ø) on a same distance from the powersupply (see table) make sure that all holes are aligned</div>	 <div>insert plugs</div>																
4	installation in case of surface mounting	 <div>connect female connector with strain relief to powersupply</div>	 <div>make correct connection with male connector in luminaire</div>	 <div>insert plugs and fix luminaire to ceiling</div>																

	technics	 			
4	installation in case of surface mounting	cover screw holes with supplied tube plugs	   		
5	installation in case of recessed mounting	after installation of the plasterkit or recessed profile, follow the next steps	use the supplied parallelogram shaped nuts and screws with countersunk heads	set the nut on top of the screw	
6	installation in case of recessed mounting	make correct connection with male connector in luminaire	fix the luminaire in the installed recessed profile		
8	pictures				
	kreon nv	Industrieweg Noord 1152 B 3660 Opglabbeek, Belgium	Tel + 32-89-81 97 80 Fax + 32-89-81 97 90	www.kreon.com mailbox@kreon.be	Rev. date: 26/10/2010 KR8530001751