














## IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS


	<p>Installation instructions for KREON - DIAPASON on-TRACK types: ku92612_, ku92611_, ku93611_, ku92610_</p> <p> <b>WARNING</b> - IMPORTANT SAFETY INSTRUCTIONS - READ AND UNDERSTAND THESE INSTRUCTIONS BEFORE STARTING INSTALLATION - SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE</p>	<p> <b>RISK OF FIRE! - RISK OF SHOCK!</b> THIS LUMINAIRE MUST BE INSTALLED TO CONFIRM WITH NEC AND ALL LOCAL ELECTRICAL &amp; BUILDING CODES &amp; PRACTICES. TO ASSURE FULL COMPLIANCE WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL</p>	<p>INSPECTOR BEFORE INSTALLATION - IN CASE OF 120V FITTING: FOR USE WITH EUTRAC 230 TRACK SYSTEM ONLY - CAUTION - TO REDUCE RISK OF A BURN DURING RELAMPING, REMOVE LUMINAIRE FROM THE TRACK BEFORE RELAMPING - DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING - ENSURE THE LUMINAIRE IS GROUNDED</p>	<p>- LUMINAIRE IS SURFACE MOUNTED ONLY - DO NOT INSTALL ANY LUMINAIRE CLOSER THAN 6" FROM ANY CURTAIN, OR SIMILAR COMBUSTABLE MATERIAL - TO REDUCE RISK OF FIRE DO NOT USE A LAMP IDENTIFIED FOR USE IN ENCLOSED LUMINAIRES - FOR INDOOR DRY LOCATIONS ONLY - DO NOT INSTALL ANY PART OF A TRACK</p>
1	<p><b>notifications</b></p> <p>SYSTEM LESS THAN 5ft ABOVE THE FLOOR - DO NOT ATTEMPT TO ENERGIZE ANYTHING OTHER THAN LIGHTING TRACK FIXTURES ON THE TRACK. - TO REDUCE THE RISK OF FIRE AND ELECTRIC SHOCK, DO NOT ATTEMPT TO CONNECT POWER TOOLS, EXTENSION CORDS, APPLIANCES, AND THE LIKE TO THE TRACK.</p> <p><b>WARNING</b> - to reduce the risk of FIRE OR INJURY:</p>	<p>- turn off power and allow to cool before replacing lamp - lamp gets HOT quickly! contact only switch/plug when turning on - do not touch hot lens, guard, reflector or enclosure - keep lamp away from materials that may burn - do not touch lamp at any time; use soft cloth; oil from skin may damage the lamp - do not operate the luminaire with a missing or damaged shield, if required</p>	<p>- this luminaire can only be used with Kreon accessories</p> <p> = CAUTION - RISK OF FIRE - do not install a lamp identified for use only in enclosed luminaires</p> <p> = grounding conductor</p> <p> min.30" = do not install any luminaire closer than 30" from wall</p> <p> = suitable for indoor dry locations only</p>	
	<p>Notice de montage pour KREON - DIAPASON on-TRACK types: ku92612_, ku92611_, ku93611_, ku92610_</p> <p> <b>ATTENTION</b> - LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION - CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES</p>	<p> <b>RISQUE D'INCENDIE! RISQUE DE CHOC!</b> - INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE - CE PRODUIT DOIT ETRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAIT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHERENTS- CONSULTER UN ÉLECTRICIEN QUALIFIÉ POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA</p>	<p>DÉRIVATION SONT ADÉQUATS - EN CAS DE 120V LUMINAIRE: UTILISER SEULEMENT AVEC EUTRAC 230 TRACK SYSTEM - COUPER L'ALIMENTATION AVANT L'ENTRETIEN ATTENTION – POUR REDUIRE LES RISQUES D'INCENDIE DURANT LE CHANGEMENT DES LAMPES, RETIRER LE LUMINAIRE DU RAIL AVANT D'Y PROCEDER. - SUPPRIMER LA LUMIERE AVANT</p>	<p>REEMPLACER L'AMPOULE - ASSURER QUE LE LUMINAIRE EST MIS À LA TERRE - MONTER LE LUMINAIRE EN SURFACE SEULEMENT - NE PAS INSTALLER DE LUMINAIRE A MOINS DE 6" D'UN RIDEAU, OU D'UN MATERIAU SIMILAIRE COMBUSTIBLE - POUR EMPLACEMENT SECS SEULEMENT - POUR RÉDUIRE LE RISQUE D'INCENDIE UTILISER UNE LAMPE INDIQUANT "CONVIENT AUX LUMINAIRE OUVERTS"</p>
	<p>- NE PAS INSTALLER UNE PARTIE DU RAIL A MOINS DE 5th AU DESSUS DU SOL - NE PAS ESSAYER DE CONNECTER SUR LE RAIL AUTRE CHOSE QU'UN APPAREIL D'ECLAIRAGE POUR RAIL - POUR REDUIRE LES RISQUES ELECTRIQUES ET D'INCENDIE, NE PAS ESSAYER DE CONNECTER DES OUTILS ELECTRIQUES, RALLONGES, ETC... AU RAIL <b>ALERTE</b> - pour réduire le risque D'INCENDIE OU DE BLESSURE:</p>	<p>- coupez l'alimentation électrique et laisser refroidir avant de remplacer l'ampoule - la lampe chauffe rapidement! - ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte - gardez le luminaire loin de matériaux qui peut brûler - ne jamais touchez l'ampoule; utilisez un chiffon doux; l'huile de la peau peut endommager l'ampoule - luminaires équipés avec un verre de</p>	<p>sécurité doivent opéré d'un verre de sécurité complet et en place - le luminaire ne peut être utilisé qu'avec des accessoires de Kreon</p>	<p> = ATTENTION - RISQUE D'INCENDIE - pas utiliser une ampoule conçue seulement pour des luminaires fermés</p> <p> = terre</p> <p> min.30" = laisser une distance d'au moins 30" du mur</p> <p> = convient aux emplacements d'intérieur et secs seulement</p>



## 2 dimensions


provide rail, max. 2 circuits 120V  
for security reasons: do not connect current  
until final installation of all luminaires

Name	Reference	Type	Voltage ⚡	L x H x φ Diapason
Diapason on-Track	ku92612_	T4 bi-pin - GY6.35 base	120 V	8" x 62/5" x 41/2"
Diapason on-Track	ku92611_	AR111 - G53 base	120 V	8" x 62/5" x 41/2"
Diapason Cover on-Track	ku93611_	AR111 - G53 base	120 V	8" x 62/5" x 41/2"
Small Diapason on-Track	ku92610_	MR16 - GU5.3 base	120 V	8" x 51/2" x 24/5"




## 3 installation


insert fixture in rail and  
fix by turning the handle




choose correct circuit for the luminaire by  
turning the wheel on the adapter




make sure that the orientation  
of the luminaire is correct




in case of Diapason AR111, connect lamp  
with clamps and fix lamp with springs



in case of Diapason Base AR111, connect  
lamp with clamps and fix lamp with spring




in case of Diapason T4 bi-pin or Small  
Diapason MR16, place lamp in lampholder




add supplied pin


## 4 lamp placement




reflector : push in cooling profile



lens, glass or filter :  
fix to frame with springs



glare preventer : push until it snaps



glare preventer + lens, glass or filter:  
use fixation spring

## 5 accessories

**6 picture**



This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.