




technics		IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS															
1	notifications	<p>Installation instructions for KREON - PROLOGE 145 surface mounted</p> <p><b>! WARNING:</b> READ AND UNDERSTAND ALL INSTRUCTIONS BEFORE STARTING INSTALLATION. SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE</p>	<p><b>! RISK OF FIRE! - RISK OF SHOCK!</b> - INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS THIS LUMINAIRE MUST BE INSTALLED TO CONFIRM WITH NEC AND ALL LOCAL ELECTRICAL &amp; BUILDING CODES &amp; PRACTICES. TO ASSURE</p>	<p>FULL COMPLIANCE WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL INSPECTOR BEFORE INSTALLATION. - DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING - ENSURE THE LUMINAIRE IS GROUNDED</p>	<p>- LUMINAIRE IS SURFACE MOUNTED ONLY - SUITABLE FOR INDOOR DRY LOCATIONS ONLY</p> <p>WARNING - to reduce the risk of FIRE OR INJURY: - turn off power and allow to cool before replacing lamp</p>												
		<p>- lamp gets HOT quickly! contact only switch/plug when turning on - do not touch hot lens, guard, reflector or enclosure - keep lamp away from materials that may burn - do not touch halogen lamp at any time; use soft cloth; oil from skin may damage the lamp - do not operate the luminaire with a missing or damaged shield, if required</p>	<p>The luminaire can only be used with Kreon accessories. <b>! CAUTION - RISK OF FIRE -</b> do not install a lamp identified for use only in enclosed luminaires (only in case of halogen lamptypes)</p> <p>This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.</p>	<p>Notice de montage pour KREON - PROLOGE 145</p> <p><b>! ATTENTION:</b> LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES</p> <p><b>! RISQUE D'INCENDIE! RISQUE DE CHOC!</b></p>	<p>- INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE - CE PRODUIT DOIT ETRE INSTALLE SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAIT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHERENTS - CONSULTER UN ELECTRICIEN QUALIFIE POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DERIVATION SONT ADEQUATS</p>												
		<p>- COUPER L'ALIMENTATION AVANT L'ENTRETIEN - ASSURER QUE LE LUMINAIRE EST MIS A LA TERRE - MONTER LE LUMINAIRE EN SURFACE SEULEMENT - POUR EMBLACEMENT SECS SEULEMENT</p>	<p>ALERTE - pour réduire le risque D'INCENDIE OU DE BLESSURE: - coupez l'alimentation électrique et laissez refroidir avant de remplacer l'ampoule - la lampe chauffe rapidement! - ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte - gardez le luminaire loin de matériaux qui peut brûler - ne jamais touchez l'ampoule halogène; utilisez un chiffon doux; l'huile de la peau</p>	<p>peut endommager l'ampoule - luminaires équipés avec un verre de sécurité doivent operé d'un verre de sécurité complet et en place, si nécessaire Le luminaire ne peut être utilisé qu' avec des accessoires de Kreon <b>! ATTENTION - RISQUE D'INCENDIE -</b> ne pas utiliser une ampoule conçue seulement pour des luminaires fermés (en cas de lampe halogène)</p>	<p>Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.</p>												
2	dimensions	<p>Prologe 145 Single</p> 			<table><tr><th>Name</th><th>Reference</th><th>L x W x H</th></tr><tr><td>Prologe 145 Single directional</td><td>ku(x)98811</td><td>51/2" x 51/2" x 61/8"</td></tr><tr><td>Prologe 145 Single directional</td><td>ku(x)98812</td><td>51/2" x 51/2" x 61/8"</td></tr><tr><td>Prologe 145 Single</td><td>ku98813</td><td>51/2" x 51/2" x 61/8"</td></tr></table>	Name	Reference	L x W x H	Prologe 145 Single directional	ku(x)98811	51/2" x 51/2" x 61/8"	Prologe 145 Single directional	ku(x)98812	51/2" x 51/2" x 61/8"	Prologe 145 Single	ku98813	51/2" x 51/2" x 61/8"
		Name	Reference	L x W x H													
Prologe 145 Single directional	ku(x)98811	51/2" x 51/2" x 61/8"															
Prologe 145 Single directional	ku(x)98812	51/2" x 51/2" x 61/8"															
Prologe 145 Single	ku98813	51/2" x 51/2" x 61/8"															
	<p>Prologe 145 Single</p>																

# kreon

## technics




Name	Reference	X - Y
Prologe 145 Single directional	ku(x)98811	411/16" - 35/32"
Prologe 145 Single directional	ku(x)98812	411/16" - 35/32"
Prologe 145 Single	ku98813	411/16" - 35/32"

## 3 installation

drill holes at correct distance and place plugs (see table)

mount ceiling box on ceiling and fixate with screws




- connect black wire from transformer to black supply wire
- connect white wire from transformer to white supply wire
- connect green grounding wire from conduit to green grounding wire from luminaire


Reference	Voltage
ku98811_, ku98812	120V > 12 V
kx98811_, kx98812	277V > 12 V
ku98813	120 V

## 4 connection

connect to correct current



**click !**




**click !**


## 5 installation

place housing over springs until click.  
don't push housing against ceiling housing

insert louvre in housing



in case of AR111 type: connect cable clamps on the AR111  
make sure the lamp is fixed on the springs



in case of T4 bi-pin type: fit required reflector on the springs



## 6 lamp placement

kreon nv

Industrieweg Noord 1152  
B-3660 Opglabbeek  
Belgium

Tel + 32 89 81 97 80  
Fax + 32 89 81 97 90

www.kreon.com  
mailbox@kreon.be

Rev. date: 26/03/2018  
KU8880031603