




technics

| Productname | Reference | Max. Power | Output Current | Mains Voltage | Forward Voltage |
|-------------------------------------|-----------|------------|----------------|---------------|-----------------|
| LED driver, 500mA, DALI / touch DIM | kr772123 | 27W | 500mA | 220V - 240V | 12V - 54Vdc |




1 specifications



L 138mm x W 67mm x H 29.5mm

2 strain relief

add the supplied strain relief to the LED driver



PRI 220...
240V
1
2
3
DA 4
DA 5

SEC LED-aux 21
LEDset 22
LED - 23
LED + 24

!! ADD THE SUPPLIED RESISTOR Rset 10kOhm E48 series

!! ALWAYS CONNECT THE RED LED STRING TO +
ALWAYS CONNECT THE BLACK LED STRING TO -
ENSURE THE DRIVER HAS NOT BEEN POWERED FOR
AT LEAST 1 MIN. BEFORE CONNECTING THE LED
CONNECT LEDS IN SERIES AND NOT IN PARALLEL
LOAD WIRES LENGTH: 2m MAX

3 connection

kreon nv

Industrieweg Noord 1152
3660 Opglabbeek
Belgium

Tel + 32 89 81 97 80
Fax + 32 89 81 97 90

www.kreon.com
mailbox@kreon.be

Revision date: 21/05/2015
KR8000002073 sheet 1/1