


kreon installation manual

technics & dimensions




name	reference	voltage VAC	frequency	led current	nom. input current driver	max. power	power factor	ØxH	H1	S	S1
holon 80 fixed gear inclusive on/off	KR96282X-XXXX-XX-SW	230V	50/60Hz	700mA	0,12A	32W	0,95	85x130	65	2,5	2,8
holon 80 fixed gear inclusive 1-10V	KR96282X-XXXX-XX-VD	230V	50/60Hz	700mA	0,15A	36W	0,95	85x130	65	2,5	2,8
holon 80 fixed gear inclusive dali	KR96282X-XXXX-XX-DD	230V	50/60Hz	700mA	0,15A	38W	0,95	85x130	65	2,5	2,8

1. light source/gear information

light source containing product


The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.



Energy Efficiency Class and EPREL-information for each specific LED/fixture can be found on the last page of this manual

gear containing product


the gear contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person



Please make sure the main voltage is disconnected before proceeding! ⚡

2. installation


use the delivered cardboard mold for the correct positioning of the installation holes



use the three indicated holes in the mold for the fixation holes

drill three holes at that position. the holes should be suitable for your chosen installation screws/plugs (not delivered with the product!)
installation holes in the holon have diameter Ø 5mm


make a cut-out to to put the cables through (cut-out in the holon = Ø20)



kreon installation manual


3. electric connection

insert the chosen fixation
pull the mains cable out of the ceiling
make sure that the wires coming out of
the ceiling have a minimum length of
140mm




connect the L&N to the 2P connector
connect the ground wire under the screw of
the earthing bracket

fix the ceilingbox to the ceiling with three
screws (not delivered!)




in case of dimming:
connect the dim wires (coming from
the cable on client side) directly to the gear
- dali has no polarity
- 1-10V: mind the polarity!
black = -
red = +




4. installation

match the springs with the cut-outs in the
ceilingbox, fix the bottompart with a
bayonet movement (clockwise)




accessories


KR762002




KR726100




KR726200




unscrew the louvre in order
to take it out of the fixture




place the accessory in
the louvre



in case of diffusing/sculpture lens:
place the structured side downwards



screw the louvre + the accessory
back in














kreon installation manual

pictures



kreon light source information

Fixture reference	LED reference	Energy Efficiency Class	QR-code	EPREL link
KR96282x-8327-SP-XX	KR7000103032	F		https://eprel.ec.europa.eu/qr/1093486
KR96282x-8327-FL-XX -WFL-XX	KR7000102745	E		https://eprel.ec.europa.eu/qr/1093540
KR96282x-8330-SP-XX	KR7000103193	F		https://eprel.ec.europa.eu/qr/1093485
KR96282x-8330-FL-XX -WFL-XX	KR7000102785	E		https://eprel.ec.europa.eu/qr/1093493
KR96282x-8340-SP-XX	KR7000103195	F		https://eprel.ec.europa.eu/qr/1093483
KR96282x-8340-FL-XX -WFL-XX	KR7000103038	E		https://eprel.ec.europa.eu/qr/1093491
KR96282x-9027-SP-XX	KR7000103890	F		https://eprel.ec.europa.eu/qr/1093514
KR96282x-9027-FL-XX -WFL-XX	KR7000103894	E		https://eprel.ec.europa.eu/qr/1093522
KR96282x-9030-SP-XX	KR7000103891	F		https://eprel.ec.europa.eu/qr/1093513
KR96282x-9030-FL-XX -WFL-XX	KR7000103895	F		https://eprel.ec.europa.eu/qr/1093521
KR96282x-9040-SP-XX	KR7000103893	F		https://eprel.ec.europa.eu/qr/1093511

Fixture reference	LED reference	Energy Efficiency Class	QR-code	EPREL link
KR96282x-9040-FL-XX -WFL-XX	KR7000103897	F		https://eprel.ec.europa.eu/qr/1093519
KR96282x-9827-SP-XX	KR7000103302	NO		
KR96282x-9827-FL-XX -WFL-XX	KR7000103039	F		https://eprel.ec.europa.eu/qr/945515
KR96282x-9830-SP-XX	KR7000103199	NO		
KR96282x-9830-FL-XX -WFL-XX	KR7000103040	F		https://eprel.ec.europa.eu/qr/945514
KR96282x-9840-SP-XX	KR7000103198	NO		
KR96282x-9840-FL-XX -WFL-XX	KR7000103042	F		https://eprel.ec.europa.eu/qr/945512

kreon replacement parts

replacement parts

exploded view

