

IMPORTANT SAFETY INSTRUCTIONS - SAVE THESE INSTRUCTIONS

Installation instructions for KREON - SMALL DIAPASON GEARBOX LED, gear inclusive, type: ku94620_

! WARNING - READ ALL INSTRUCTIONS - UNDERSTAND ALL INSTRUCTIONS BEFORE STARTING INSTALLATION - SAVE THESE INSTRUCTIONS FOR FUTURE REFERENCE

! ENSURE THE LUMINAIRE IS GROUNDED RISK OF FIRE! - RISK OF SHOCK!
- INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS THIS LUMINAIRE MUST BE INSTALLED TO CONFIRM WITH NEC AND ALL LOCAL ELECTRICAL & BUILDING CODES & PRACTICES. TO ASSURE FULL COMPLIANCE

WITH LOCAL CODES AND REGULATIONS, CONSULT WITH YOUR LOCAL ELECTRICAL INSPECTOR BEFORE INSTALLATION.
- DISCONNECT POWERSUPPLY BEFORE INSTALLING OR SERVICING
- LUMINAIRE IS SURFACE MOUNTED ONLY
- SUITABLE FOR DAMP LOCATIONS

WARNING - to reduce the risk of FIRE OR INJURY:
- turn off power and allow to cool before replacing lamp
- lamp gets HOT quickly! contact only switch/plug when turning on
- do not touch hot lens, guard, reflector or enclosure
- keep lamp away from materials that may

1 notifications

burn
- this luminaire can only be used with Kreon accessories

Notice de montage pour KREON - SMALL DIAPASON GEARBOX LED, auxiliaire inclus, type: ku94620_

! RISQUE D'INCENDIE! RISQUE DE CHOC!

POUR VOUS ASSURER QUE LES CONDUCTEURS DE LA DÉRIVATION SONT ADÉQUATS
- COUPER L'ALIMENTATION AVANT L'ENTRETIEN
- MONTER LE LUMINAIRE EN SURFACE SEULEMENT
- CONVIENT AUX EMPLACEMENTS HUMIDES


This installation manual might not cover all details or variations. When additional information is required, please contact your local representative, or one of the Kreon offices.

! ATTENTION - LIRE ET COMPRENDRE TOUTES LES INSTRUCTIONS AVANT L'INSTALLATION - CONSERVER CES INSTRUCTIONS POUR DE FUTURES REFERENCES


- INSTRUCTIONS RELATIVES À UN RISQUE D'INCENDIE OU DE BLESSURE
- CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAIT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHERENTS
- CONSULTER UN ÉLECTRICIEN QUALIFIÉ

ALERTE - pour réduire le risque D'INCENDIE OU DE BLESSURE:
- coupez l'alimentation électrique et laissez refroidir avant de remplacer l'ampoule
- la lampe chauffe rapidement!
- ne touchez pas l'objectif à chaud, la garde, le réflecteur ou une enceinte
- gardez le luminaire loin de matériaux qui peut brûler
- le luminaire ne peut être utilisé qu'avec des accessoires de Kreon

Cette notice de montage ne couvre pas tous les détails ou les variations. Pour des informations supplémentaires veuillez contacter votre représentant local ou un des bureaux Kreon.



Small Diapason LED



Diapason gearbox


2 dimensions

Name	Reference	Type	L x W x Ø
Small Diapason Base	ku94620_	LED 8.4W 700mA	4" x 5 1/2" x Ø 2 4/5"
Small Diapason Base	kx94620_	LED 8.4W 700mA	4" x 5 1/2" x Ø 2 4/5"


the small diapason gearbox is designed to fit on an octagonal conduit box size 4

input ku94620_ is 120Vin and the included driver is triac phase dimmable
input kx94620_ is 120-277Vin and the included driver is 0-10V dimmable


technics




align and install octagonal conduit
box size 4



use allen key to open
the gearbox




connect supply wires to fixture wires
with proper size wire nuts (by others)




ku94620x = 120V and TRAIC dimmable
kx94620x = 120-277V and 0-10V dimmable

2 dimensions

- connect black wire from gearbox to black supply wire
- connect white wire from gearbox to white supply wire
- connect green grounding wire in from conduit to green grounding wire from gearbox




fix the gearbox on the conduit box



close the gearbox again

3 installation



the gearbox can also be used
for surface mounted raceway tubing

4 alt. installation